



# MODEL CS-1 MAGNESIUM ANODE SIMULATOR

## FEATURES:

- 1.7 Volts DC Output
- Adjustable Output Current
- 1 Milliamp Resolution LCD Display
- Simulates a Standard Mag. Anode
- Internal Replaceable Battery
- Provides "What if..." on Pipelines
- Weather Resistant, Lockable Case

**AVAILABLE  
FROM STOCK**



*The CS-1 portable Mag. Anode Simulator is an ideal DC current source that will allow the user to see what the addition of a mag anode on their system will do to Pipe to Soil measurements and other CP tests.*

Distributed by:



**TECNOLOGÍA TOTAL**  
[www.tecnologiatotal.net](http://www.tecnologiatotal.net)

[teststations.com](http://teststations.com)

[detectron.com](http://detectron.com)

**[Info@tinker-rasor.com](mailto:Info@tinker-rasor.com) | [tinker-rasor.com](http://tinker-rasor.com)**

Tinker & Razor quality is found in our products, our people and our customer service.

# TINKER & RASOR

## PRODUCT DATA SHEET | MODEL CS-1 MAG. ANODE SIMULATOR

### FEATURES:

- 1.7 Volts DC Output
- Adjustable Current Output
- LCD display of output, 1mA resolution
- Replaceable batteries
- Portable
- Lightweight, only 3.5 lbs

### CONSTRUCTION:

- Near indestructible case
- Weather sealed
- Lockable
- Built for rugged use

### APPLICATIONS:

- CP Current Requirements
- CP Maintenance Tests

### ENVIRONMENT:

0°C to 50°C (32°F to 122°F)

### SPECIFICATIONS:

- Output Range: 0 Amp 1.7 Amp
- Continuous Operation

### DIMENSIONS:

8.25" x 6.5" x 3.25", 3.5 lbs  
(209mm x 165mm x 82.5mm, 1.58kg)

### SHIPPING DIMENSIONS:

13" x 7.5" x 5", 5 lbs  
(330mm x 190.5mm x 127mm, 2.26kg)

**DELIVERY:** Immediately from STOCK  
F.O.B. New Braunfels, TX USA

**SERVICE:** 24-hour Turn-Around

**TERMS:** Net 30 Days, on approval of credit

**WARRANTY:** 90 Days, parts and labor

### MODEL CS-1 PANEL



### MODEL CS-1 VIEWS

**AVAILABLE FROM STOCK**

[tinker-rasor.com](http://tinker-rasor.com)



**TECNOLOGÍA TOTAL**  
[www.tecnologiatotal.net](http://www.tecnologiatotal.net)