

# MODEL VC-2 The Verifier

VERIFIES ACCURACY OF VOLTMETERS

### **FEATURES:**

- Very Accurate Voltage Output
- 1mv, 10mv, 100mv, 1v,2.5v & 5v
- Use with any Manufacturers Voltmeter
- Annual Calibration Cycle



Connect to your voltmeter to ensure your meter is in calibration.





teststations.com

detectron.com

Info@tinker-rasor.com | tinker-rasor.com



# INKER & RASOR

## PRODUCT DATA SHEET | EXPLORING ELECTRODES

#### **FEATURES:**

- Portable, battery operated
- Highly accurate DC Output
- Verify any DC Voltmeter
- Battery test LED

#### **APPLICATIONS:**

Verify voltmeter readings

#### **RECOMMENDATIONS:**

Use with T&R Models CPV-2 and CPV-4 Use with any DC voltmeter

#### **ENVIRONMENT:**

-10°C to 50°C (14°F to 122°F)

#### **SPECIFICATIONS:**

#### **OUTPUTS:**

0.001v (+/- 1mV)

0.01v (+/- 1mV)

0.1v (+/- 1mV)

1.0v (+/- 5mV)

2.5v (+/- 5mV)

5.0v (+/- 5mV)

(6) "AA" cell alkaline batteries

#### **DIMENSIONS:**

6.25" x 4" x 2.5", 1.5lbs (158mm x 101mm x 63mm, 0.7kg)

#### **SHIPPING DIMENSIONS:**

4.5" X 4.5" x 5.75", 3 lbs

(114.3mm x 114.3mm x 146mm, 1.4kg)

**DELIVERY: Immediately from STOCK** 

F.O.B. New Braunfels, TX USA

SERVICE: 24-hour Turn-Around

**TERMS:** Net 30 Days, on approval of credit

WARRANTY: 90 Days, parts and labor



EASY TO USE | COMES WITH CABLES
ANNUAL CALIBRATION RECOMMENDED



**SHOWN IN OPERATION WITH CPV-4 VOLTMETER** 

**AVAILABLE FROM STOCK** 

tinker-rasor.com